# HOBBYVĚC

## Návod na připojění k Wifi v softvéru LaserGRBL.



Grbi	Archivo	Colores	Idioma	Herramientas	:	
IP:PORT	192.168.0.	102:23			<b>S</b>	12
Archivo						
Progreso						-
es WiFi (	Discovery					
		This tool al connected Press "Sca	lows you to via WiFi. m <sup>''</sup> button	o search for the IP Scan the network to start.	that your network I and try to check if I	has assigned to your engraver the connection port is available.
IP A	ddress	Ping	Host N	lame	MAC Address	Connection (Port 23)

1. Ujistěte se, že je USB připojeno k přístroji a je zadáno v okně konzoly.

#### Zadejte do konzole : **\$73=3**

uaserGRBL v5.4.0	
Grbl File Colors Language Too	ols ?
COM COM3 V Baud 115200 V	1400
Progress 1 ÷	
\$73=3	20
@ [MSG:25:Info: USB SERIAL STREAM CO_     @ AlgoLaser Alpha Ready!     @ ALF:109.	· · ·
@ ALH:AIgOLASER AM VI.2. @ ALM:GENERAL.	1 00g
@ Grb1HAL 1.1f ['\$' or '\$HELP' for h SH	
	1250 -

2. Následně zadejte následovný příkazy.

#### \$74=(Název vaši WIFI sítě) \$75=(Heslo WIFI sítě)

(např. název mé domácí sítě Wi-Fi: FOTOVECI heslo sítě Wi-Fi: 88888888)



3. Chcete-li obnovit stav a získat adresu IP, zadejte **\$WRS**. Pokud se připojení nezdaří, zkontrolujte, zda je WiFi správné. Chcete-li zobrazit celou IP adresu, posuňte stavový řádek doleva nebo doprava.



4. Klikněte na Settings - Usb Serial - Telnet - Uložit.

<b>\$</b>	Disconnect	119200 - 🌜	8	Frot	ocol Raster import Veo	tor inport Jog control Automat
😭 🏠	Reset Homing Unlock		5		Grbl ~	Fireware type - Grbl: the avesore firmware f - Snoothie [experimental]: support - Marlin [experimental]: support - VigoVork [experimental]: support
8 0 3	Grbl Configuration Settings Material DB	ENI COUNCIED)	<u> </u>		UsbSerial V UsbSerial UsbSerial2 Telnet LaserVebESP8266	Connection Frotocol: - UsbSerial: is the most commo - UsbSerial2: an alternative i - Telnet: if you have a ViPi-T - LaterVebESPE206: support BiP
••	Laser Lifespan Hotkeys	for help]	100 · · ·		Eaulator	Streaming Mode: [Default Buffe - Buffered: optimize ormands - Synchronous: vait for the ex - BepeatOnBrror: same as Sync
×	Exit GG:79:Hanning: WIFI STA	s setting has changed, reboot.	12%		UltraFast ~	Threading Mode: UltraFact, Fas This setting affect the speed Set slover values if you are e
S \$7	SG:79:Warning: WIFI STA	s setting has changed, re.			Zasue detector	LaserGRBL can detect issues an If disabled all the issues are
🖉 Sn 💌 ( M	V SATS				Soft Reset [Ctrl-I]	If enabled LaserGADL send a so
[VGG:75:10f0: WIFI STA LLOP TRYING CONNECT] [VSG:70:10(0: WIFI AP STORED]					Hard Reset	If enabled LaserGABL send a he
	GG:G9:INfo: WIFI AP READ SG:70:INfo: WIFI AP STOP GG:69:INfo: WIFI AP READ	//////////////////////////////////////			Query \$1 at connect	In enabled LazerGABL zend a \$1 Please do not disable this fee
щ (И С. (И	66:74:Info: WIPI STA ACT 66:77:Info: Get IP 192.1	[00,252.60]	KLL			1

5. Ujistěte se, že počítač se systémem LightBurn je připojen ke stejné WiFi nebo LAN.



6. Odpojte se od gravírky - Klikněte na Grbl - Wifi discovery - Scan - Klikněte na Available.

Landinun A2413		
Grbl Fio Colors Language Jools ?     PORT 100212723     enume     sgress     sgress	WeitDisconcery This tool allows you to soutch for the IP the your engresser connected vis Will Scan the ne councelies port is available. Fress 'Scan' button to sturt. If Address Fing Host Fune NUC Address 192.100.252.00 JFres Toidf: al.e7 192.100.252.01 Jes Eas eside: 50:10	t yver network bas assigned t tworh and toy in cheek is the Connection (Fort Areidable Failed Failed
050:74(2010) 1072 514 467793]]   050:77(2010) 061 20 102.160.252.08]	Som finished 7.7 fort 22 2	C1000605 5080

### 7. Úspěšně připojeno.

🖕 LaserGRBL v5.4.0	- 0	×
Grbl <u>File Colors Language Tools</u> ?		
P:PORT 192.168.252.60:23	S 0.000 Y: F: 00000 S	0.00 5:00
Algolaser Alpha Ready! ALF:109. ALH:Algolaser AM V1.2. ALH:SERERAL. GrblHAL 1.1f ['5' or 'SHELP' for help]		
	g - - - - - - - - - - - - -	